

## Pedlock® Magnum™ Pedestals (CPLM)

# Buried copper distribution pedestals offering greater splicing capabilities with the good-housekeeping Magnum backboard

Amphenol Charles Pedlock Magnum Pedestals (CPLM) provide superior environmental protection of copper buried distribution points in the outside plant. CPLM Pedestals are designed for universal use, with a good-house-keeping backboard that offers greater splicing areas and many convenient attachment points for terminal blocks and other hardware, with optional ladder bar attachments for large cable bundle storage.

CPLM Pedestals feature a non-metallic PVC construction that won't rust, corrode, chip or fade. A lift-off locking dome not only provides technician- friendly 360° access to internal working areas, but also creates a "Bell-Jar" effect that protects internal components from floods.

A variety of offered sizes and accessories ensure the right fit for every application, including splice points, subscriber distribution points, and transmission access locations.





**CPLM** 

Pedestal Diameter	Max. Splice Capacity
6"	350 pairs
8"	350 pairs
10"	350 pairs

CPLM 10 shown with a typical connect and drop arrangement (joined pairs hung on ladder bars on the CO side, 25-pair terminal block mounted on drop side)





#### **FEATURES**


- · Three diameters: 6', 8' and 10'
- Durable, noncorrosive, green PVC construction
- 360° access to cable and apparatus
- Universal backboard for good housekeeping with built-in aluminum ground plate, cable attachments and optional offset terminal grounds
- Locking bolt for security (216 tool)
- Service wire channel secures and protects feed and drop cables (excludes intergral base)
- Meets or exceeds industry standards for durability and long service life
- Mounting hardware provided
- Optional 2-piece rehab (split) base available for easy rehabilitation of damaged pedestals without disrupting splice bundle
- Optional self-locking dome prevents accidental dome displacement from high water rise when CPLM is not locked properly
- Pole, stake or stand-alone installation
- Beveled bottom cutout design on optional integral stakes provide for easy, stable installations




**Broadband Cable** 

## **Product Outline Dimensions**

### **CPLM Series 2 Round Base with Stake Dimensions**







#### All dimensions are in inches

Size	Α	В	С	D	E	F	G	н
6"	7.4"	27.4"	38.4"	34.4"	26.9"	61.3"	31"	7.8"
8"	8.9"	27.2"	38.2"	34.2"	26.9"	61.1"	31"	9.3"
10"	11.7"	27.2"	38.2"	34.2"	27"	61.2"	31"	12"

### **CPLM Series 2 Integral Stake Dimensions**





### All dimensions are in inches

Size	Α	В	С	D	E
6"	7.4"	27.4"	34.4"	24"	58.4"
8"	9.1"	27.2"	34.2"	24"	58.2"
10"	11.7"	27.2"	34.2"	24"	58.2"



## **Ordering Information**

Part Number	<u>Description</u>
CPLM 6	6" Pedestal, round base, Magnum backboard, service wire channel
CPLM 8	8" Pedestal, round base, Magnum backboard, service wire channel
CPLM 10	10" Pedestal, round base, Magnum backboard, service wire channel
CPLM 6-I	6" Pedestal, integral stake base, Magnum backboard, service wire channel
CPLM 8-I	8" Pedestal, integral stake base, Magnum backboard, service wire channel
CPLM 10-I	10" Pedestal, integral stake base, Magnum backboard, service wire channel
CPLM 6-R	6" Pedestal, rehab (split) base, Magnum backboard, service wire channel
CPLM 8-R	8" Pedestal, rehab (split) base, Magnum backboard, service wire channel
CPLM 10-R	10" Pedestal, rehab (split) base, Magnum backboard, service wire channel

#### **PEDESTAL ACCESSORIES**

Part Number	Description
002271F	Standard 6" copper dome assembly, 6" X 26.5"
003151F	Standard 8" copper dome assembly, 8" X 26.5"
002295F	Standard 10" copper dome assembly, 10" X 26.5"
80-001106-F	Complete backboard for 6" CPLM
80-001156-F	Complete backboard for 8" CPLM
80-001109-F	Complete backboard for 10" CPLM
97-PKOR06-A	6" orange high visibility cap (50 pieces)
97-PKORo8-A	8" orange high visibility cap (50 pieces)
97-PKOR10-A	10" orange high visibility cap (50 pieces)
043110F	6" rehab (split) Magnum base assembly
043114F	8" rehab (split) Magnum base assembly
043130F	10" rehab (split) Magnum base assembly
24-100946-F	Service wire channel kit, 2.5" X 12.5" (25 pieces)
18-900731-F	Rectangular drop channel plug kit (25 pieces)
010376-F	1.25" black rubber base grommet plug (25 pieces)
PHP10	10" base hole plug; PVC green (100 pieces)
PHP68	6" & 8" base hole plug; PVC green (100 pieces)
97-500504-A	6" ladder bar kit (50 pieces)
97-500505-A	8" ladder bar kit (50 pieces)
97-500506-A	10" ladder bar kit (50 pieces)
041919F	Molded Magnum D-Clip kit (100 pieces)
UMS30-STD	Metal mounting stake and hardware, 30" Length



Rehab (Split) Base



Service Wire Channel Kit



**High-Visibility Cap** 

#### Charles Industries, LLC

An Amphenol Company 1450 American Lane, 20th Floor, Schaumburg, IL 60173

Metal mounting stake and hardware, 36" Length

Metal mounting stake and hardware, 42" Length

Universal pole mounting bracket kit



UMS36-STD

UMS<sub>42</sub>-STD

UMB102A

mktserv@charlesindustries.com



(847) 806-6300



